Version: A

2016-3-2

# Specification for Approval

Customer:	
Model Name:	

Sı	Customer approval		
R&D Designed	R&D Approved	QC Approved	
Peter	Peng Jun		

Version: A

2016-3-2

## **Revision Record**

REV NO.	REV DATE	CONTENTS	Note
Α	2016-3-2	NEW ISSUE	

Version: A

2016-3-2

## **Table of Contents**

List	Description	Page No.
	Cover	1
	Revision Record	2
	Table of Contents	3
1	Scope	4
2	General Information	4
3	External Dimensions	5
4	Interface Description	6
5	Absolute Maximum Ratings	7
6	Electrical Characteristics	7
7	Timing Characteristics	8
8	Backlight Characteristics	10
9	Optical Characteristics	11
10	Reliability Test Conditions and Methods	13
11	Handling Precautions	14
12	Precaution for Use	15
13	Packing Method	15



Version: A

2016-3-2

### 1. Scope

This specification defines general provisions as well as inspection standards for TFT module supplied by AMSON electronics.

If the event of unforeseen problem or unspecified items may occur, naturally shall negotiate and agree to solution


#### 2. General Information

ITEM	STANDARD VALUES	UNITS
LCD type	3.5"TFT	
Dot arrangement	240(RGB)×320	dots
Top Polarizer Type	Anti-Glare	
Display mode	TFT/ Transflective	
Viewing Direction	6 O'clock	
Driver IC	ILI9341V	
Module size	61.00(W)×85.00(H)×2.93(T)	mm
Active area	53.64(W)×71.52(H)	mm
Dot pitch	0.2235(W)×0.2235(H)	mm
Interface	SPI+18BIT RGB	
Operating temperature	-20 ~ +70	°C
Storage temperature	-30 ~ +80	°C
Back Light	6 White LED	
Weight	TBD	g

Version: A

2016-3-2

#### 3. External Dimensions





Version: A

2016-3-2

### 4. Interface Description

PIN NO.	PIN NAME	DESCRIPTION				
1	VL1	Anode of LED(High voltage)				
2	GND	Power ground				
3	VL2	Cathode of LED(Low voltage)				
4	GND	Power ground				
5	VSHD	Power supply for digital				
6-8	GND	Power ground				
9	VSYNC	Vertical sync. in RGB mode				
10	GND	Power ground				
11	RESET	Reset(Low active)				
12-14	GND	Power ground				
15	CS	Chip select input(Low enable)				
16	GND	Power ground				
17	SDO	Serial data output				
18	SDI	Serial data input				
19	GND	Power ground				
20	SCL	Serial interface clock				
21	GND	Power ground				
22-27	B5~B0	Blue data bus				
28	ENAB	Display enable pin from controller				
29	GND	Power ground				
30	HSYNC	Horizontal sync. in RGB mode				
31	GND	Power ground				
32	DCLK	Pixel clock signal in RGB mode				
33	GND	Power ground				
34-39	G5~G0	Green data bus				
40	GND	Power ground				
41-46	R5~R0	Red data bus				
47-50	GND	Power ground				



Version: A

2016-3-2

5. Absolute Maximum Ratings

Item	Symbol	Min.	Max.	Unit
Logic Supply Voltage	VSHD	-0.3	4.5	V
Analog Supply Voltage	VSHD	-0.3	4.5	V
Supply current (One LED)	ILED		30	mA
Operating Temperature	Тор	-20	70	°C
Storage Temperature	Тѕт	-30	80	°C
Storage Humidity	HD	20	90	%RH

### 6. DC Characteristics


Item	Symbol	Min.	Тур.	Max.	Unit	Remark
Logic Supply Voltage	VSHD	3.0	3.3	3.6	V	-
Analog Supply Voltage	VSHD	3.0	3.3	3.6	V	-
Input High Voltage	V <sub>IH</sub>	0.7 VSHD	-	VSHD	V	-
Input Low Voltage	V <sub>IL</sub>	GND	-	0.3 VSHD	V	-
I/O Leak Current	lu	-1	-	1	uA	-

Version: A

2016-3-2


### 7. Timing Characteristics

### 7.1 3-WIRES SPI Timing Diagram



Signal	Symbol	Parameter	min	max	Unit	Description
W/4	tscycw	Serial Clock Cycle (Write)	100	-	ns	400
	tshw	SCL "H" Pulse Width (Write)	40	<u> </u>	ns	
001	tslw	SCL "L" Pulse Width (Write)	40	8	ns	
SCL	tscycr	Serial Clock Cycle (Read)	150		ns	
	tshr	SCL "H" Pulse Width (Read)	60	-	ns	
	tsir	SCL "L" Pulse Width (Read)	60	-	ns	
SDA / SDI	tsds	Data setup time (Write)	30		ns	
(Input)	tsdh	Data hold time (Write)	30	- 2	ns	
SDA / SDO	tacc	Access time (Read)	10	-	ns	
(Output)	toh	Output disable time (Read)	10	50	ns	
	tscc	SCL-CSX	20	3	ns	
CSX	tchw	CSX "H" Pulse Width	40	-	ns	
tcss tcsh	tcss	CSX-SCL Time	60	-	ns	
	tcsh	CSX-SCL Time	65	-	ns	


Note: Ta = 25 °C, VDDI=1.65V to 3.3V, VCI=2.5V to 3.3V, AGND=VSS=0V



Version: A

2016-3-2

### 7.2 RGB Timing Diagram



Characteris	tice	Symbol	Mi	n.	Ty	p.	Ma	ax.	Unit
Characteris	oucs	Syllibol	24 bit	8 bit	24 bit	8 bit	24 bit	8 bit	Oilit
DOTCLK Frequen	cy	fDOTCLK	0.70	7.0	6.5	19.5	10	30	MHz
DOTCLK Period		tDOTCLK )	100	33.3	154	51.3	- 2	1927	ns
Horizontal Frequen	ncy (Line)	/\fh\	32	3	14	.9	22	.35	KHz
Vertical Frequency	(Refresh)	< fV)	10-	ej .	6	0	9	0	Hz
Horizontal Back Po	orch	(HBP	-	-	68	204	-	583	tDOTCLK
Horizontal Front P	orch	tHFP		-	20	60	-	0.50	tDOTCLK
Horizontal Data St	art Point	tHBP	724	25	68	204	- 25	1027	tDOTCLK
Horizontal Blankin	g Period	tHBP + tHFP	10-2	29	88	264	144	왕복합	tDOTCLK
Horizontal Display	Area	HDISP	19-20	(4)	320	960	120	7-2	tDOTCLK
Horizontal Cycle		Hcycle	-	-50	408	1224	450	1350	tDOTCLK
Vertical Back Porc	:h	tVBP	- 10		1	8			Lines
Vertical Front Pord	h	tVFP	32	S	4	1	, 7%;	97	Lines
Vertical Data Start	Point	tVBP	tVBP - 18		18		3.23		
Vertical Blanking F	Period	tVBP + tVFP	10-	ei.	2	2	1 %		Lines
Madian Disales	NTSC	68			24	10			1
Area –	PAL	VDISP			280(PALM=0)		1 9	-	Lines
	PAL	>6				288(PALM=1)			
NTSC		Vausla	100	8	26		21	-n	Lines
Vertical Cycle	PAL	Vcycle	N		31	13	350		Lines



Version: A

2016-3-2

### 8. Backlight Characteristic



Item	Symbol	MIN	TYP	MAX	UNIT	Test Condition	
Supply Voltage	Vf	-	19.2	-	V	If=20mA	
Supply Current	If	-	20	30	mA	-	
Luminous Intensity for LCM	-	-	150	-	Cd/m <sup>2</sup>	If=20mA	
Uniformity for LCM	-	80	-	-	%	If=20mA	
Life Time	-	30000	50000	-	Hr	If=20mA	
Backlight Color	White						




Version: A

2016-3-2

9. Optical Characteristics

Item	Conditions		Min.	Тур.	Max.	Unit	Note	
	Horizontal	θL	1	40	-			
Viewing Angle	Tionzoniai	θR	-	45	-	dograe	(1) (2) (6)	
(CR>10)	Vertical	θт	-	40	-	degree	(1),(2),(6)	
	vertical	θв	-	55	-			
Contrast Ratio	Center		100	150	-	-	(1),(3),(6)	
Posnonso Timo	Rising		ı	35	-	ms	(1),(4),(6)	
Response Time	Falling		-	35	-	ms	1),(4),(6)	
	Red x		ı	-	-	-		
	Red y		-	-	-	-		
	Green x	Green x		-	-	-		
CF Color Chromaticity	Green y		-	-	-	-	(1) (6)	
(CIE1931)	Blue x	Blue x		-	-	-	(1), (6)	
,	Blue y		-	-	-	-		
	White x		-	0.31	_	-		
	White y		-	0.32	-	-		
Transmittance			-	-	_	%	(1),(6)	


Note (1) Measurement Setup: The LCD module should be stabilized at given temp. 25°C for 15 minutes to avoid abrupt temperature change during measuring. In order to stabilize the luminance, the measurement should be executed after lighting backlight for 15 minutes in a windless room.



Version: A

2016-3-2

Note (2) Definition of Viewing Angle




Note (3) Definition Of Contrast Ratio (CR)

The contrast ratio can be calculated by the following expression Contrast Ratio (CR) = L63 / L0

L63: Luminance of gray level 63, L0: Luminance of gray level 0

Note (4) Definition of response time



Note (5) Definition of Transmittance (Module is without signal input)

Transmittance = Center Luminance of LCD / Center Luminance of Back Light x 100%

Note (6) Definition of color chromaticity (CIE1931)

Color coordinates measured at the center point of LCD



Version: A

2016-3-2

10. Reliability Test Conditions and Methods

NO.	TEST ITEMS	TEST CONDITION	INSPECTION AFTER TEST
1	High Temperature Storage	80°C±2°C×120Hours	
2	Low Temperature Storage	-30°C±2°C×120Hours	
3	High Temperature Operating	70°C±2°C×120Hours	Inspection after 2~4hours storage at room temperature, the samples should be free from defects: 1, Air bubble in the LCD. 2, Seal leak. 3, Non-display. 4, Missing segments. 5, Glass crack. 6, Current IDD is twice higher than initial value. 7, The surface shall be free from damage. 8, The electric characteristic requirements shall be satisfied.
4	Low Temperature Operating	-20°C±2°C×120Hours	
5	Temperature Cycle(Storage)	-20°C $\Longrightarrow$ 25°C $\Longrightarrow$ 70°C (30min) (30min) 1cycle Total 10cycle	
6	Damp Proof Test (Storage)	50°C±5°C×90%RH×120Hours	
7	Vibration Test	Frequency:10Hz~55Hz~10Hz Amplitude:1.5M X,Y,Z direction for total 3hours (Packing Condition)	
8	Drooping Test	Drop to the ground from 1M height one time every side of carton. (Packing Condition)	
9	ESD Test	Voltage:±8KV,R:330Ω,C:150PF,Air Mode,10times	

#### **REMARK:**

- 1, The Test samples should be applied to only one test item.
- 2, Sample side for each test item is 5~10pcs.
- 3,For Damp Proof Test, Pure water(Resistance >  $10M\Omega$ )should be used.
- 4,In case of malfunction defect caused by ESD damage, if it would be recovered to normal state after resetting, it would be judge as a good part.
- 5, EL evaluation should be accepted from reliability test with humidity and temperature: Some defects such as black spot/blemish can happen by natural chemical reaction with humidity and Fluorescence EL has.
- 6, Failure Judgment Criterion: Basic Specification Electrical Characteristic, Mechanical Characteristic, Optical Characteristic.

### 11. Handling Precautions



Version: A

2016-3-2

### 11.1 Mounting method

The LCD panel of AMSON TFT module consists of two thin glass plates with polarizes which easily be damaged. And since the module in so constructed as to be fixed by utilizing fitting holes in the printed circuit board.

Extreme care should be needed when handling the LCD modules.

#### 11.2 Caution of LCD handling and cleaning

When cleaning the display surface, Use soft cloth with solvent

[Recommended below] and wipe lightly

- Isopropyl alcohol
- Ethyl alcohol

Do not wipe the display surface with dry or hard materials that will damage the polarizer surface.

Do not use the following solvent:

- Water
- Aromatics

Do not wipe ITO pad area with the dry or hard materials that will damage the ITO patterns Do not use the following solvent on the pad or prevent it from being contaminated:

- Soldering flux
- Chlorine (CI), Sulfur (S)

If goods were sent without being sili8con coated on the pad, ITO patterns could be damaged due to the corrosion as time goes on.

If ITO corrosion happen by miss-handling or using some materials such as Chlorine (CI), Sulfur (S) from customer, Responsibility is on customer.

#### 11.3 Caution against static charge

The LCD module use C-MOS LSI drivers, so we recommended that you:

Connect any unused input terminal to POWER or GROUND, do not input any signals before power is turned on, and ground your body, work/assembly areas, and assembly equipment to protect against static electricity.

#### 11.4 packing

- Module employs LCD elements and must be treated as such.
- Avoid intense shock and falls from a height.
- To prevent modules from degradation, do not operate or store them exposed direct to sunshine or high temperature/humidity

#### 11.5 Caution for operation

- It is an indispensable condition to drive LCD's within the specified voltage limit since the higher voltage then the limit cause the shorter LCD life.
- An electrochemical reaction due to direct current causes LCD's undesirable deterioration, so that the use of direct current drive should be avoided.
- Response time will be extremely delayed at lower temperature then the operating temperature range and on the other hand at higher temperature LCD's how dark color in them. However those phenomena do not mean malfunction or out of order with LCD's, which will come back in the specified operation temperature.
- If the display area is pushed hard during operation, some font will be abnormally displayed but it resumes normal condition after turning off once.
- Slight dew depositing on terminals is a cause for electro-chemical reaction resulting in terminal open circuit.
  - Usage under the maximum operating temperature, 50%Rh or less is required.

### 11.6 storing



Version: A

2016-3-2

In the case of storing for a long period of time for instance, for years for the purpose or replacement use, the following ways are recommended.

- Storage in a polyethylene bag with the opening sealed so as not to enter fresh air outside in it. And with no desiccant.
- Placing in a dark place where neither exposure to direct sunlight nor light's keeping the storage temperature range.
- Storing with no touch on polarizer surface by the anything else.
   [It is recommended to store them as they have been contained in the inner container at the time of delivery from us

### 11.7 Safety

- It is recommendable to crash damaged or unnecessary LCD's into pieces and wash off liquid crystal by either of solvents such as acetone and ethanol, which should be burned up later.
- When any liquid leaked out of a damaged glass cell comes in contact with your hands, please wash it off well with soap and water

#### 12. Precaution for Use

#### 12.1

A limit sample should be provided by the both parties on an occasion when the both parties agreed its necessity. Judgment by a limit sample shall take effect after the limit sample has been established and confirmed by the both parties.

#### 12.2

On the following occasions, the handing of problem should be decided through discussion and agreement between responsible of the both parties.

- When a question is arisen in this specification
- When a new problem is arisen which is not specified in this specifications
- When an inspection specifications change or operating condition change in customer is reported to AMSON TFT, and some problem is arisen in this specification due to the change
- When a new problem is arisen at the customer's operating set for sample evaluation in the customer site.

### 13. Packing Method

**TBD**